

Appendix B — Word Table

Values V1 and V2 are used to identify the words when programming.

<u>Word</u>	<u>V1</u>	<u>V2</u>	<u>Word</u>	<u>V1</u>	<u>V2</u>	<u>Word</u>	<u>V1</u>	<u>V2</u>
zero	0	0	I	8	15	status	7	8
one	0	1	Igor	3	12	T	9	10
two	0	2	intrusion	3	14	telemetry	7	9
three	0	3	J	9	0	telephone	7	10
four	0	4	Joe	3	15	temperature	2	2
five	0	5	K	9	1	This is	7	11
six	0	6	kilovolts	4	2	time	7	12
seven	0	7	kilowatts	4	3	to	7	13
eight	0	8	L	9	2	transmitter	7	14
nine	0	9	Larry	4	4	triggered	7	15
ten	0	10	limit	4	5	U	9	11
eleven	0	11	local	4	6	upper	8	1
twelve	0	12	lower	4	7	V	9	12
thirteen	0	13	M	9	3	version	8	2
fourteen	0	14	main	4	8	volts	8	3
fifteen	0	15	malfunction	2	1	W	9	13
A	8	7	manual	4	9	water	1	13
action	1	0	memory	4	10	watts	8	4
address	1	1	milliamps	4	14	Woofer	8	5
advanced	1	2	millivolts	4	15	X	9	14
alarm	1	3	milliwatts	5	0	Y	9	15
AM	1	4	minutes	5	1	year	8	6
amperes	1	5	Moe	5	3	Z	10	0
audio	1	7	month	5	5	25 ms voice pause	10	5
auto	1	6	N	9	4	50 ms voice pause	10	6
auxiliary	1	11	network	5	4	100 ms voice pause	10	7
B	8	8	night	5	7	200 ms voice pause	10	8
basic	1	8	normal	5	8	500 ms voice pause	10	9
Billy Bob	1	9	number	5	9	,	10	14
Bozo	1	10	nyuk nyuk nyuk	2	9	;	10	2
C	8	9	O	9	5	:	10	3
channel	1	12	off	5	10	/	10	1
code	1	15	OK	5	11	=	10	13
command	2	0	on	5	12	CR	10	11
control	2	3	Oscar	5	14	CR&LF	10	10
Curly	2	4	P	9	6	&	10	4
D	8	10	percent	5	15	+++	10	12
day	2	5	percent power	6	0	DTMF 0	10	15
degrees	2	7	point	6	1	DTMF 1	11	0
digit	2	8	pound	6	3	DTMF 2	11	1
E	8	11	power	6	5	DTMF 3	11	2
enter	2	10	programming	6	7	DTMF 4	11	3
error	2	11	push	6	8	DTMF 5	11	4
exit	2	13	Q	9	7	DTMF 6	11	5
F	8	12	R	9	8	DTMF 7	11	6
failure	2	14	ratio	6	10	DTMF 8	11	7
fire	3	0	reflected	1	14	DTMF 9	11	8
FM	3	1	reprogram	6	11	3.95 second voice pause	11	9
G	8	13	ring	6	12			
Gary	3	3	S	9	9			
Gonzo	3	4	scan	6	14			
goodbye	3	5	security	6	15			
H	8	14	sequence	7	1			
Hal	3	7	site	7	2			
hello	3	8	software	7	3			
here	3	9	Spanky	7	4			
hours	3	11	speaking	7	5			